

After starting the router, connect the computer with the included cable to the LAN port. Being connected to the router, open the web browser and enter the address <http://192.168.0.1>. Log in to the default data, i.e. login: admin, leave the password field blank.

Product Page : DIR-300 Hardware Version : B1 Firmware Version : 2.02

D-Link

LOGIN
Log in to the router:

User Name Password

Domyślnie
login: admin
hasło: puste

WIRELESS

PPPOE configuration

Click on Setup, then on Internet setup. As My internet connection we set up PPPOE and enter our login and password. Set the other highlighted options as in the picture below.

DIR-300 // **SETUP** **ADVANCED** **MAINTENANCE** **STATUS** **HELP**

Internet Setup **INTERNET CONNECTION**

Use this section to configure your Internet Connection method. There are several connection methods to choose from: Static IP, DHCP, PPPoE, PPTP, L2TP, Russian PPTP(Dual Access) and Russian PPPoE(Dual Access). If you are unsure of your connection method, please contact your Internet Service Provider.

Note: If using the PPPoE option, you will need to remove or disable any PPPoE client software on your computers.

Save Settings Don't Save Settings

ACCESS POINT MODE

Use this to disable NAT on the router and turn it into an Access Point.

Enable Access Point Mode

INTERNET CONNECTION TYPE

Choose the mode to be used by the router to connect to the Internet.

My Internet Connection is : **PPPoE (Username / Password)**

PPPOE

Enter the information provided by your Internet Service Provider (ISP).

Dynamic PPPoE Static PPPoE

User Name : **mojlogin**

Password : *********

Confirm Password : *********

Service Name : _____ (optional)

IP Address : _____

MAC Address : _____ - _____ - _____ - _____ - _____ - _____ (optional)

Clone MAC Address

Receive DNS from ISP Enter DNS Manually

Primary DNS Address : _____

Secondary DNS Address : _____ (optional)

Maximum Idle Time : 5 Minutes

MTU : 1492

Connect mode selected : **Always** New Schedule

Manual Connect-on demand

Helpful Hints..

- Internet Connection:** When configuring the router to access the Internet, be sure to choose the correct **Internet Connection Type** from the drop down menu. If you are unsure of which option to choose, please contact your **Internet Service Provider (ISP)**.
- Support:** If you are having trouble accessing the Internet through the router, double check any settings you have entered on this page and verify them with your ISP if needed.

You can now plug the internet cable into the INTERNET / WAN port and plug the router into a socket. By default, the data for a wireless network is usually found on a sticker on the bottom of the device.