

Step 1

Choose your connection type (Wired or Wireless)

Step1a: If Wireless, connect to your TP-Link wireless network. Find the wireless network (named TP-LINK_XXXXXX by default which is printed on the label of the router) from the WiFi list on your device and connect it with the wireless password (default password is printed on the router's label as well).

Step1b: if Wired connect your Ethernet cable to one of the LAN ports on the back of your TP-Link router.

Step 2

Open a web browser (i.e Safari, Google Chrome or Internet Explorer). At the top of the window in the address bar, type in <http://tplinkwifi.net>.

Note:

The default access address differs by model. Please find it on the bottom label of the product.

Step 3

Type the username and password in the login page. The default username and password For TP-Link devices is admin.

Note:

All letters for both username and password will be lower case.

If you forgot your username or password to login, please find reset button/hole and reset it to the factory default settings.

Once you log into the web-based Utility (Management Page), you can change settings of your router, such as create a new wireless password etc.

Step 4

Configure WAN Connection Type

On the router's management page, click Network > WAN on the left of the web page:

Change the WAN Connection Type to PPPoE.

Step 5

Enter your PPPoE username and password which are provided.

The screenshot shows the WAN configuration interface. At the top, there is a green header with the text "WAN". Below this, the "WAN Connection Type" is set to "PPPoE/Russia PPPoE" in a dropdown menu, which is highlighted with a red box. To the right of this dropdown is a "Detect" button. Underneath, the "PPPoE Connection" section is also highlighted with a red box and contains three input fields: "User Name" with the value "username", "Password" with masked characters "*****", and "Confirm Password" with masked characters "*****". Below the PPPoE section, the "Secondary Connection" is set to "Disabled" with radio buttons for "Dynamic IP" and "Static IP". The "Wan Connection Mode" section has "Connect on Demand" selected, with a "Max Idle Time" of "15" minutes. Other options include "Connect Automatically", "Time-based Connecting" (with a time range from 00:00 to 23:00), and "Connect Manually" (with a "Max Idle Time" of "15" minutes). At the bottom of the configuration area, there are "Connect" and "Disconnect" buttons, and the status is shown as "Disconnected!". At the very bottom of the page, there are "Save" and "Advanced" buttons, with the "Save" button highlighted by a red box.

Step 6

Click Save to save your settings, then the router will connect to Internet after a while.